

## Magnetic + shock and vibration detector

✓ GRADE 2

- Magnetic + VESTA shock and vibration detector
- Supervises the opening / closing of doors
- Works on glass, wood, metal, and concrete
- Tamper tamper
- It works with 1 3V CR123 lithium batteries
- 5 year battery life
- EN50131 Grade 2



### Reference / Model

**VESTA-060N / DCSV-29-F1**

### Characteristics

Detects door / window openings, glass breakage and shock detection  
Three adjustable sensitivity threshold levels (high, medium and low)  
RF frequency: 868MHz  
Tamper switches  
Programming of security and home automation systems  
Creation of scenes to switch on / off appliances  
Remotely adjustable door / window material and sensitivity  
Suitable for wood, glass, metal and concrete  
Wide RF range, faster signal transmission  
Wireless for easy installation  
Supervisory signals ensure proper operation  
Works with 1 3V CR123 lithium batteries  
Battery life of up to 5 years  
-10 ° C ~ + 45 ° C operating temperature  
Relative humidity up to 85% (non-condensing)  
Dimensions: 31 (W) x 93.5 (H) x 22.5 mm  
EN50131 Grade 2, Class II certified