VESTA-373

SR-35-F1

Interior alarm via radio

ØGRADE 2

- Indoor radio alarm of 95dB at 1 meter
- Remote programming
- Fire and burglary sounds
- Programmable 3/5/10 minutes
- Periodic supervision signals
- Tamper protection
- EN50131 Grade 2 Certificate



| Reference / Model | VESTA-373 / SR-35-F1 |
|---|----------------------|
| Output level of 95dB at 1 meter | |
| Possibility of remote programming | |
| Differentiated sounds for intrusion and fire | |
| Lightweight and flexible to install | |
| Programmable alarm siren with 3/5/10 minute durations | |
| Audible notifications of arming, disarming and low battery status | |
| Periodic supervisory signals to verify system integrity | |
| Tamper protection prevents unauthorized removal and sabotage | |
| Low battery detection | |
| Compatible with VESTA F1 Alarm Panels | |
| RF frequency: 868MHz | |
| Power supply: 2 AA lithium L91 batteries | |
| Battery life up to 3 years | |



VESTA-373

SR-35-F1

Interior alarm via radio

| \$ | /=sta® |
|-----------|--------|
|-----------|--------|

| Reference / Model | VESTA-373 / SR-35-F1 |
|--|----------------------|
| Operating temperature -10°C \sim +45°C | |
| Relative humidity up to 85% (non-condensing) | |
| Dimensions: 105 (W) x 105 (H) x 31 mm | |
| CE compliant | |

EN50131 Grade 2 Certificate